

Display modes

PS24VJ operates in two display modes: *grid mode* and *full mode*.







Use the *grid mode* to load footages and check their placements, then switch to *full mode* to mix them together.

Cursors




In grid mode, each of the 2 video layers is symbolised by a cursor. The active cursor, the one you control is colored in green. In full mode, the 2 displayed videos are the one selected by the two cursors.

Grid mode controls

Use the right analog stick to scroll the grid and the cross pad to move the active cursor


	swap cursor control
	swap cursors
	switch to full mode
	play backward/forward
	open the browser
hold 	pause

Browser Controls

↓/↑	up and down
←	open parent folder
→	open folder or load highlighted file
	open all files from a folder
	open the options menu
	close the browser

Options menu controls

From the options menu, you can swap between single and 2 players mode, save and load snapshots of the current grid.

	close Options menu
→	confirm
←	cancel

Full mode controls



Use the left analog stick to assign a blend mode between the 2 layers.

↑	alpha channel blend (or black chroma key if the top layer has no alpha channel)
→	mix blend
↓	multiplication blend
←	addition blend

Click the stick to cancel the current blend mode.







use the right analog stick to control the speed

↑	faster
↓	slower

use the right analog stick for light effects










←	fade to black
→	white flash

Use the cross pad to move the active cursor considering its grid position

	switch to grid mode
	switch between loop and ping pong modes
	play backward/forward
	switch to grid mode, open the load menu
	swap layer control
	swap layers order

Full mode video filters













turn on/off geometry filters

	+ 		mirror filter
	+ 		scrolling filter
	+ 		glitch filter







adjust geometry filters directions

	+ 	↑/→/↓/←	mirror filter
	+ 	↑/→/↓/←	scrolling filter
	+ 	↑/→/↓/←	glitch filter

turn on/off color filters

	+ 		extreme contrast filter
	+ 		negative filter
	+ 		game boy color palette filter
	+ 		hue filter

adjust color filters options

	+ 	↑/→/↓/←	extreme contrast filter
	+ 	↑/→/↓/←	negative filter
	+ 	↑/→/↓/←	hue filter

Links

PS24VJ official page

<http://www.pikilipita.com/ps24vj>

Other projects: Pikilpita Advance, Pikix, Super Pikix...

<http://www.pikilipita.com>

Contact

pikilipita@pikilipita.com